PROJECT HASH

CHECKLIST

Pool setup sheet

Pool, worker and backup settings for one miner, on one page.

ACCOUNT AND PAYOUT

- [ ] Open the pool account on the pool's own site, with your own email.
- [ ] Turn on two-factor sign-in and save the recovery codes offline.
- [ ] Paste the payout address. Compare the first and last six characters with your wallet.
- [ ] Check that the address is for the coin this machine mines.
- [ ] Read the smallest payout and work out how many days your machine needs to reach it.

Pool _____ Account name _____

Payout address, last six characters _____ Smallest payout _____

POOL 1: THE SETTINGS

- [ ] Use the server nearest to the machine.
- [ ] Use the port for this coin.
- [ ] If the pool shows nothing, try the address with and without the part before the host name.
- [ ] Keep the worker name short: letters and numbers, no spaces.

Stratum URL and port _____ Worker _____

Password field _____

POOLS 2 AND 3: THE BACKUPS

- [ ] Pool 2: the same pool, another server.
- [ ] Pool 3: another company, with an account and a payout address already set.
- [ ] Save, let the miner restart, and look at the status of all three.
- [ ] Test it once: give pool 1 a wrong port, watch the miner move over, then put it right.

Pool 2: URL and worker _____ Pool 3: URL and worker _____

FIRST DAY

- [ ] After a few minutes: pool 1 is active and accepted shares are counting up.
- [ ] After an hour: the worker is online on the pool’s page and every board shows on the miner.
- [ ] After 24 hours: the pool’s one-day hashrate is close to the rating.
- [ ] Rejected and stale shares together stay under one in a hundred.
- [ ] The alert for an offline worker is on, and you received its test message.

Hashrate on the miner after 24 hours _____ Hashrate on the pool after 24 hours _____

Rejected shares _____

THE MACHINE

- [ ] The default password of the miner’s page is changed.
- [ ] The IP address is reserved in the router.

Model and version _____ Serial number _____

IP address _____ Firmware version _____

Date _____

NOTES

General guidance. Where your maker's manual or terms differ, follow them.